



## **APPLICATION MANAGER 2G/3G**

How to delete an applet?

1. In CardAdmin, right-click on the card icon to open the contextual menu. Select the "Application download" for 2G or 3G module from the contextual menu.

😚 Card Adr	nin - [GemXplorer]	
File Media	Tools Window Help	
2	2 📴 📚 희 🗈 🔊 🍳	) 🕘 🎱 🔯 🍏
⊕ 🐼 GemXp	lore 3G V3 0-256K - Card Manager mode - Gemr Card Settings File	
	Select Mode	
	Exchange APDU	
	Trace 🕨	
	Warm Reset	
	Card Information	
	Trace (Secured)	
	Application Download 2G	Download (Reset activated)
	Application Download 3G	Download (Reset deactivated)

2. In the target window select the card you are using.

🌋 Application Manager 2G (Reset activa	ted) in 2G mode - GemXplore 3	G V3.0-256K - Gemplus USB Smart Card Re	. 🗖 🗖 🔀
2 1 1 1 1 1 1 1	Terminal : Gemplus USB Smart Card R	eader 0 👽 🃂 🛛 BIP OTA I/O	9 🛛
2G applications	Actions  Load Package Load Package & Install Applets Install Applets Delete Instances & Package Delete Instances Delete Package	Target GemXplore 3G V2.1 64K PK GemXplore 3G V2.2 128K PK GemXplore 3G V3.0 GemXplore 3G V3.1 GemXplore Generations Plexible GemXplore Generations option CDMA GemXplore World 32K GemXplore World 64K GemXplore Xpresso V3 32K GemXplore Xpresso V3 64K GemXplore Xpresso V3 64K PK	

3. Select the reader your card is placed in

🎽 Application Manager 2G (Re	eset deactivated) in 2G mode -
😬 🛅 🛍 🐘 👰 🔟 🥬	🔍 🔳 Terminal : Gemplus USB Smart Card Reader 0 🔜 🗡
· · · · · · · · · · · · · · · · · · ·	Gemplus USB Smart Card Reader 0
2G applications	Actor Texas Instruments SmartCardSlot 0
🖃 🤀 jsr177	Load Package GemXplore Wo
🖃 🇭 Anniet	🔚 🔄 Load Package & Install Applets 🔢 GemXnlore Xn

4. Click on the zoom icon to see the contents of the card.



5. You will se the OP Browser window

🧏 OP Browser				
Package View		Instance View		
🫅 jsr177	A0 00 00 00 62 B0 BA A3 01	₿ jsr177	A0 00 00 00 62 B0 BA A3 81	
Free non volatile mem	ory : Not available.	Free volatile me	emory : Not available.	
	🗹 System AlDs hidden	Refresh Delete	Close Help	

6. Select the package and than the instances you want to remove. Then click on the Delete button

<mark>ች</mark> OP Browser					
Package View			Instance View		
🗀 jar177	A0 00 00 00 62 B0 BA A3 01		🗋 jsr177	A0 00 00 00 62 B0 BA A3 81	
Status: LOADED			Status: SELEC	TABLE	
Privilege: no privilege			Privilege: no	) privilege	
Free non volatile memory : Not available. Free volatile memory : Not available.					
	🗹 System AlDs hidden	Refresh	Delete Clo	ose Help	

7. You will see the "Confirm Delete Operation" window. Click on OK to confirm the deletion.

Confirm Delete Ope	ration			
Packages to Delete		Instances to Del	lete	
🗀 jar177 🛛 AO OO OO O	0 62 B0 BA A3 01	📑 jær177	A0 00 00 00 62 B0 BA A3 81	
	ОК	Cancel		

## 8. You may close "OP Browser" window now

🤏 OP Browser	
Package View	Instance View
Free non volatile memory : Not available.	Free volatile memory : Not available.
System AlDs hidden Refresh	Delete Close Help