

Release Notes for Cisco Video Surveillance Manager, Release 7.10

Revised: November 29, 2017



.



Figure 6 *Configure VBR Predicted Bitrate*

- Step 3** Verify that Storage Retention Dashboard warning is cleared ([Figure 7](#)).
- a. Click **Monitor Video**.
 - b. Click **Storage Retention Dashboard**.
 - c. Select a Media Server and select the camera.
 - d. Verify that the status icon is green.
 - e. Verify that Storage Retention Status is “OK”.

Usage Notes

- Storage retention is supported only for continuous recordings. However the user will also be able to view storage retention statistics for continuous + motion based recordings. The data will be accurate





Cisco Connected Safety and Security UCS Platform Series Servers

Cisco VSM Release 7.10 is pre-installed on new instal

-

Additional Notes on Arecont Devices

- AV20185, AV20365, AV12186, AV8365 and AV8185 are 4-channel IP cameras. In order to support multiple video channels from a single device, Cisco VSM 7 models these devices as “Encoders”.
-





Obtaining and Installing Licenses

To install a license, purchase the license and obtain the license file, then upload the file to the Operations Manager.

[Table 28](#) lists the part numbers for the Cisco VSM licenses. Multiple camera and VSMS licenses can be

Understanding the Cisco VSM Software Types

[Table 29](#) describes the different types of software and fi

Resolved Caveats

[Table 31](#) lists caveats that are resolved in this release.

Related Documentation

See the following locations for the most current information and documentation:

Cisco Video Surveillance 7 Documentation Roadmap

Descriptions and links to Cisco Video Surveillance documentation, server and storage platform documentation, and other related documentation.

